


Battery Heater Kits



Applicable Models

- 12RES
- 14RESA (120 and 240 Volts)
- 14RESAL
- 20RESC (120 and 240 Volts)
- 20RESCL
- 20RESD
- 24/30RCL

- 38/48/60RCL
- 38RCLB
- 48RCLB
- 60RCLA
- 80-100ERESD
- 125-150ERESC

Description

The battery heater kit includes a battery heating wrap to help increase the battery temperature in cold climates. The battery heater is connected to a thermostat for controlled heating. When temperatures fall below $16^{\circ}C$ ($60^{\circ}F$), the thermostat turns the heater on, maintaining optimum battery temperature. The thermostat turns the heater off at $27^{\circ}C$ ($80^{\circ}F$).

Battery heater kits are recommended for generators installed in regions where the temperature regularly falls below 0° C (32° F).

Note: Battery is not included with heater kit.

KOHLER.

KOHLER CO., Kohler, Wisconsin 53044 USA Phone 920-457-4441, Fax 920-459-1646 For the nearest sales and service outlet in the US and Canada, phone 1-800-544-2444 KOHLERPower.com

Specifications

| Kit Number | GM92406-KP2-QS | GM92406-KP3-QS | GM104703-KP1 |
|-------------------------------|----------------|----------------|--------------|
| Volts | 240 | 120 | 120 |
| Heater wrap rating, Watts | 50 | | 65 |
| Battery wrap length, mm (in.) | 864 (34) | | 1067 (42) |
| Power cord length, mm (in.) | 1830 (72) | | 1677 (66) |
| Thermostat on temperature | 16°C (60°F) | | |
| Thermostat off temperature | 27°C (80°F) | | |

Kit Selection

| Kit Number | Generator Set Models* | |
|--|--|--|
| GM104703- KP1 | 24/30RCL 38RCLB 48RCLB 60RCLA 80- 100ERESD 125- 150ERESC | |
| GM92406-KP2-QS | 14RESA (240 Volts) 20RESC (240 Volts) | |
| GM92406-KP3-QS | 12RES 8/10/12RESV/RESVL 14RESA/RESAL (120 Volts) 20RESC/RESCL (120 Volts) 20RESD | |
| * Current Residential/Light Commercial models shown. | | |

DISTRIBUTED BY:

Availability is subject to change without notice. Kohler Co. reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever. Contact your local Kohler[®] generator set distributor for availability.

© 2013, 2014, 2015, 2016, 2018 by Kohler Co. All rights reserved.